

WHS0900 Configurable Stock Location Enquiry

Aptean Ltd
Copyright © 2011-2026.

Contents

1 WHS0900 Configurable Stock Location Enquiry.....	1
--	---

1 WHS0900 Configurable Stock Location Enquiry

The Configurable Stock Location Enquiry screen is intended to display stock quantities summarised at a pallet level with the additional option of drilling down into individual pallet records for more detailed information.

It is a useful enquiry tool to give a quick overview of current stock levels and any outstanding movements associated with the product.

The enquiry is executed after the following parameters have been entered: -

- **Location Use Type** - Default is all types, with the option to specify a particular type such a stock by owner in a pick face
- **Owner** - Will default in the users current owner code, a List of Values (LOV) is available to select an alternative valid owner code if required
- **Stock** - It is possible to directly enter a valid stock code into the field or to call a LOV to select a product code

The screen will display the details in the tabs below:

- *Stock By Area*

- *Stock By location*



Stock Location Enquiry

Owner: ROB Warehouse: NFT

10-JUN-2025 WHS0900 v4.23

Owner: ROB	001 RM	Stock: SC02 Stock Code 02 Description 2 of SC02 Description 3 of SC02	Pack					
AKA Code:								
Location Use Type:								
Stock By Area		Stock By Location						
Selection All Areas								
Move	Pallet	Rotation No	Cust Rotation	Location	On Hand	Free	Weight	Free Weight (KG)
	47176	1212	1212	01113	50/ 0	50/ 0	117 250	117 250
	47177	1212	1212	01113	50/ 0	50/ 0	117 250	117 250
	47179	1212	1212	01113	50/ 0	50/ 0	117 250	117 250
	47180	1212	1212	01113	50/ 0	50/ 0	117 250	117 250
	47172	1212	1212	01114	50/ 0	50/ 0	117 250	117 250
	47173	1212	1212	01114	48/ -10	48/ 0	110 215	112 560
	47174	1212	1212	01132	50/ 0	50/ 0	117 250	117 250
	47178	1212	1212	01132	50/ 0	50/ 0	117 250	117 250
	47181	1212	1212	01132	50/ 0	50/ 0	117 250	117 250
	47175	1212	1212	C1603	50/ 0	50/ 0	117 250	117 250
	47173	1212	1212	MA011	0/ 10	0/ 0	2 345	0.000
	5201	200700563	200700563	01015	20/ 0	20/ 0	46 900	46 900

Pallet Details Configure

From *Stock By Location*, you can drill down to pallet details WHS0902 below.

Pallet Details - WHS0902

Displays a more detailed view of the pallet, including the status of the stock quantities, audit numbers for movements and any hold codes and its associated information.

Stock Location Enquiry

Owner: ROB Warehouse: NFT

10-JUN-2025 WHS0902 v4.22

Owner: ROB	001 RM	Bonded: N	Country of Origin:
Stock: SC02	Stock Code 02 Description 2 of SC02 Description 3 of SC02	Pack	
Pallet: 47176	Cust Pallet: 6055	Location Code: 01113	Usage: BULK
On Hand: 50/ 0	Weight: 117 250 KGM	Rotation: 1212	Receipt Number: 7003
Held: 0/ 0	Weight: 0.000 KGM	Cust Rotation no: 1212	Date: 15-MAR-2019
Committed: 0/ 0	Weight: 0.000 KGM		
Allocated: 0/ 0	Weight: 0.000 KGM		
Free: 50/ 0	Weight: 117 250 KGM	Sell-By Date: 23-MAY-2025	Catch Weight: 0.000 KGM
Trans In: 0/ 0	Weight: 0.000 KGM	Manu Date:	Stock Take In Progress: N
Trans Out: 0/ 0	Weight: 0.000 KGM	Movement Number: 0	To: []
Reason Code: Hold Description Held Held Weight Hold Reference Review Date Time Overlap			

Pallet Movements Pallet Labels

You can configure which items are displayed in the screen by using the **Configure** button provided.



User Name: SCE Program Id: WHS0917

Label	Width	Required
Rotation No	88	
Owner	68	
SubCode	20	
Name	140	
Pallet Id	52	
Cust Pallet	104	
Cust Rotation No	124	
On Hand Qty	82	
On Hand Weight	56	
Free Qty	82	
Free Weight	56	
U.O.S.	76	
U.O.M	44	
Stock	128	
Description	136	
Pallet Type	30	

Field Label	Width	Seq No
Owner	68	1
Stock	128	2
Pallet Id	52	3
Cust Pallet	104	4
Rotation No	88	5
Cust Rotation No	124	6
On Hand Qty	82	7
Free Qty	82	8

This screen allows you to specify which fields should be displayed, their sequence and the width that will be displayed in the Stock Location Enquiry form, giving a more user friendly look.

The screen will show all configurable elements for the screen being configured. For example, if this is configuring the columns shown on results from [WHS0917](#), this will be shown in the program ID on the top right.

The screen consists of two tables:

- Shown columns
- Available but not shown columns.

The arrow buttons allow you to select which fields you require and then to sequence the fields within the display. It is then possible if required to enter into the Width field and set the length of individual fields to save on the displayed space.

When finished, save your configuration and close the screen.

